



## Quick Look

---

Number of Ethernet WAN port

**0 / 1 (GE) <sup>[1]</sup>**

[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BRI-MINI-FP) is required to activate the perpetual license for the aforementioned features.

Number of Ethernet LAN port

**3 / 2 (GE) <sup>[1]</sup>**

[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BRI-MINI-FP) is required to activate the perpetual license for the aforementioned features.

Router Throughput

**300Mbps <sup>[2]</sup>**

[2] Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP.

SpeedFusion VPN Throughput (No Encryption)

**80Mbps <sup>[2]</sup>**

[2] Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP.

SpeedFusion VPN Throughput (256-bit AES)

**60Mbps <sup>[3]</sup>**

[3] 60 Mbps by default for Firmware 8.4.1 or above. Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP.

Number of Cellular Modem

**1**

## Interfaces

---

Maximum Ethernet WAN / LAN port configuration

**1 WAN with 2 LAN,  
0 WAN with 3 LAN**

SFP LAN / WAN

**No**

Serial Interface

**No**

Wi-Fi AP

**No**

Wi-Fi WAN **No**

USB WAN **No**

Module Expansion **No**

## Performance

---

Number of Recommended Users **1-60**

Maximum Number of Controlled AP  
/ Switch **No**

## Wireless details

---

Cellular Modem Category options **1x 5G**

5G support **Yes**

SIM Slots **2**

SIM Card Size **Nano-SIM (4FF)**

Wi-Fi Radio **No**

Wi-Fi Antenna Transmit Power  
(2.4GHz, single chain) **No**

Wi-Fi Antenna Transmit Power  
(5GHz, single chain) **No**

Multiple SSIDs **No**

GPS **No**

RemoteSIM (used in SIM Injector) **Yes (HW2+)**

FusionSIM **Yes (HW2+)**

Peplink eSIM Data Plans **Yes**

BYO eSIM **Yes**

## Features

---

SpeedFusion Hot Failover	<b>Yes</b> <sup>[1]</sup>	[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.
SpeedFusion Smoothing	<b>Yes</b> <sup>[1]</sup>	[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.
SpeedFusion Bandwidth Bonding	<b>Yes</b> <sup>[1]</sup>	[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.
SpeedFusion Connect	<b>Yes</b> <sup>[4]</sup>	[4] PrimeCare subscription includes 500 GB/year complimentary SpeedFusion Connect Usage data.
SpeedFusion Relay Mode (Server)	<b>Yes</b>	
Drop-In Mode	<b>Yes</b>	
High Availability	<b>Yes</b>	
Peplink AP Series Management	<b>No</b>	
Remote AP & Multiple Config Profiles Management	<b>No</b>	
Switch Controller	<b>No</b>	
WAN as LAN	<b>Yes</b>	
LAN Bypass	<b>No</b>	
InTouch	<b>Yes</b>	
Virtual WAN	<b>Yes</b> <sup>[5]</sup>	[5] 1 Virtual WAN complimentary with active PrimeCare. Up to 3 Virtual WAN upon purchasing Virtual WAN Activation Licence.
Synergy Mode (Controller)	<b>Yes</b>	
Synergized Device	<b>Yes</b>	
Application and Web Blocking	<b>Yes</b>	

Web Content Filtering	<b>Lite</b>	
IP Passthrough	<b>Yes</b>	
IPv6	<b>No</b>	
x.509 Certificate	<b>Yes</b> <small>[6]</small>	<small>[6] Require IPsec X.509 Certificate License Key.</small>
Captive Portal	<b>Yes</b>	
GPIO	<b>Yes</b>	
Ignition Sensing	<b>Yes</b>	
Netflow Support	<b>Yes</b>	
LACP (802.3ad) NIC Bonding	<b>No</b>	
Jumbo Frame Support	<b>No</b>	
Internal Storage for Edge Computing	<b>No</b>	
External Storage via USB Port	<b>No</b>	
Dead Reckoning	<b>No</b>	

## Core Functionality

---

Inter-VLAN Routing	<b>Yes</b>
802.1q VLANs Supported	<b>16</b>
Port-Based VLAN	<b>Yes</b>
Load Balancing Algorithms	<b>8</b>
Load Balancing & Failover	<b>Yes</b>
Inbound Load Balancing	<b>No</b>
InControl 2 Cloud Management	<b>Yes</b>

InControl GPS Fleet Management	<b>Yes</b>
--------------------------------	------------

## Advanced QoS Functionality

---

Bandwidth Usage Monitoring	<b>Yes</b>
QoS for VoIP and E-Commerce	<b>Yes</b>
User Groups Bandwidth Control	<b>Yes</b>

## VPN Functionality

---

SpeedFusion VPN	<b>Yes</b>	
Number of SpeedFusion VPN Peers	<b>2 or 5</b> <sup>[7]</sup>	[7] 2 SpeedFusion VPN Peers are enabled by default. 5 SpeedFusion VPN Peers are enabled with PrimeCare Subscription, complimentary for the first year.
IPsec VPN	<b>Yes</b>	
Number of IPsec Tunnels	<b>5</b>	
L2TP VPN / Open VPN / PPTP VPN Server	<b>Yes</b>	
Maximum PPTP / L2TP / OpenVPN Users	<b>3</b>	
Remote RADIUS / LDAP authentication in Remote User Access	<b>No</b>	
Number of OpenVPN Tunnel (Site to Site)	<b>5</b>	
Number of GRE Tunnel (Site to Site)	<b>5</b>	

## Hardware

---

Enclosure	<b>Compact, Indoor Metal</b>
4pin Molex Micro-Fit Connector	<b>Yes</b>

Terminal Block Power Connector for  
Mobile / Vehicular Deployment

**No**

AC Adapter or PSU

**AC Input 100V–240V, [8]**

[8] Compatible with ACW-632.

**DC Output 12V 2A**

Input voltage

**DC 10–30V**

PoE Input

**Yes [9]**

[9] 1x 802.3at PoE.

PoE Output

**No**

USB Power Input

**No**

Nominal Power Consumption

**11W**

Maximum Power Consumption

**13W**

Dimensions in inches

**4.95 x 4.2 x 1.4 inches**

Dimensions in mm

**125.7 x 107 x 35 mm**

Weight (Pound)

**0.93 pounds**

Weight (Gram / Kilogram)

**420 grams**

Operating Temperature

**-40°–149°F,  
-40°–65°C**

Humidity

**15%–95% (non-condensing)**

Rack-mount

**No**

Dual Hot Swap Power Supply

**No**

## Warranty Info

---

Warranty

**1-Year Limited Warranty**